

Characteristics of RTD

Model : SE-1001



SINCOM SE-1001 Characteristics of RTD is a versatile and all-inclusive trainer designed for studying the characteristics of RTD (Resistance Temperature Detector). It offers the convenience of adjusting the DC supply voltage and includes on-board digital instruments such as a DC voltmeter, DC ammeter, and temperature indicator. Additionally, it features an electrical heating system for practical experimentation. This comprehensive trainer provides a complete learning experience for understanding the behaviour and properties of RTDs.

Features

- ❖ Platinum RTD
- ❖ Wide Temperature Range
- ❖ 3^{1/2} Digit LED Digital DC Volt and Current Indicator
- ❖ Digital Temperature Indicator
- ❖ External Electrical Heating System
- ❖ Current controlling resistor in series
- ❖ In-Built Fixed and Variable regulated DC Power Supply
- ❖ Presents a multi-color Circuit Diagram printed on the front panel of the white board
- ❖ Enclosed in an attractive, light weight, High Quality, Poly Coated Imported Pine Wooden cabinet
- ❖ Interconnections by 2mm high quality banana sockets and pins.

Technical Specifications

- | | |
|-----------------------------------|-----------------------------|
| ▪ AC Mains Power Supply | : 230V \pm 10%, 50Hz |
| ▪ Fixed Regulated DC Power Supply | : +5V /500mA |
| ▪ Variable DC Power Supply | : Variable 0 to +12V |
| ▪ Temperature Sensor | : RTD PT 100 |
| ▪ Heating Source | : Electrical Heating system |
| ▪ Temperature Range | : Upto 100°C |



An ISO 9001:2015 Co.

▪ Current Controlling Resistor	: MFR 100Ω, ±5% in series
▪ Maximum Forward Current	: 100mA
▪ Maximum Output Voltage	: 12V
▪ Total Digital Meters	: 03 (1 Voltmeter, 1 Milliammeter and 1 Temperature)
▪ Digital Voltmeter	: DC 0-20V, Red Color 3 ^{1/2} Digit LED Display
▪ Digital Milliammeter	: DC 0-100mA, Red Color 3 ^{1/2} Digit LED Display
▪ Digital Temperature Indicator	: 3 ^{1/2} Digit LED Temperature Display upto 100°C with sensor
▪ Weight	: 3.0 kg (approx)
▪ Dimensions (mm)	: L 220 x W 270 x H 110
▪ Interconnections	: 2mm Banana sockets
▪ Operating Temperature	: 0-100°C, 80% RH

Learning Scope

- To study construction of RTD.
- To study the change in Resistance w.r.t. change in Temperature.
- To Observe and note the change in Voltage (V) and Current (I) of RTD w.r.t. change in Temperature.
- To Plot Temperature Vs Resistance characteristics.

Other Instruments Required : Digital Multimeter

Accessories Included : Electrical Heating System, Digital Temperature Indicator with sensor, RTD, Set of Patch Cords, Detail Instruction Manual